

1780 Patch Antenna

870-960 + 1710-2170 MHz / 5.00m RG-58 FME female

ANTENNA TYPE	Dual frequency self-adhesive linear patch-antenna for in-car screen mounting * SMALL SIZE – LOW PROFILE * SIMPLE INSTALLATION
FREQUENCY	870-960 + 1710-2170 MHz (DECT/UMTS)
IMPEDANCE	Nom. 50 Ohm
POLARISATION	Linear
GAIN	0/0 dBi
BANDWIDTH	See 'FREQUENCY'
VSWR	< 2.0 at frequency resonance
MAX. POWER	10 Watt
COLOUR	Black
DIMENSIONS	Approx. Ø 53 x 8 mm
WEIGHT	Approx. 50 g
MOUNTING	On screen (in-car use only)
MATERIAL	ABS, PE and PCB

CABLE / CONNECTOR	5 m RG58 with FME (f) connector
-------------------	---------------------------------

SPAR PARTS	RE-INSTALATION KIT	Art. No. K-1780/81-R
------------	--------------------	----------------------

